



1	Skil	1810-01, 1815-04, 1820-04, 1823, 1825-04, 1840, 1845-02	5	Porter Cable	PC7310 (Laminate Trimmer)
1	Craftsman	(315.) 175020, 175040, 175050, 175070, 17574 (09) 17511, 17515, 17528, 17533, 26834 (09) 17540, 17541, 17542, 17517	7	DeWalt	DW621
1	Porter Cable	PC690, PC7529, PC8529, PC890, PC893PK	8	Ryobi	RE180PL*
1	DeWalt	DW618, DW610	9	Bosch	PO600
1	Black&Decker	RP400	9	Dremel	963-01 («Advantage» Plunge Base)
1	Milwaukee	5615-29, 5615-21, 5616, 5619	10	Festool	900, 1000, 1010
1	Bosch	1604, 1618	11	Hitachi	M12V
1	Hitachi	M12VC	12	DeWalt	DW625
1	Freud	FT1700	12	Fein	FT-1800
1	Rigid	2900 Series	12	ELU	177
2	DeWalt	DW616	13	Bosch	1613EVS
2	Craftsman Pro	26835	14	Bosch	1617
2	Makita	3606	15	Ryobi	RE600
2	Freud	FT2000E			
2	Triton	TRC001			
3	Craftsman	27500			
4	Craftsman	(315.)275.000			

This is not intended to demonstrate all possible routers that can be used with the Milescraft base plate. Other routers not listed may fit using varied combinations of holes and slots.

- In some instances shown above, NOT ALL holes in a router's base will match the mounting pattern.
- Only 2 holes matched to a router's base are required (as a minimum) for proper installation and operation.
- You may decide to modify an existing hole or slot or add a hole(s) to better suit your router.
- The screws supplied may not fit your router. If you supply your own screws, DO NOT use "counter sink head" styles.
- *Ryobi model RE180PL uses 2 special screws that are not provided. Contact customer service at info@milescraft.com or (847) 683-9200 to receive them at no charge. Please include your mailing information in your request.
- Check our website at www.milescraft.com for possible revisions to this mounting key or other information.
- 7 in. Base Plate is included in most Milescraft® TurnLock™ router products.
(e.g. 1203 Circle/Edge Guide, 1205 Offset Base, 1206 SignCrafter, 1212 SignPro, 1207 Design/Inlay Kit)

A note about TurnLock™ Guide Bushings:

- Your TurnLock™ Guide Bushings are injection molded parts and designed for a "snug fit".
- Upon first use, you may find the fit to be somewhat tight.
If this is the case: work the bushing back and forth in the base to "seat" and "work fit" the bushing.